## Dr.coffee

# Coffeebar Plus



The metallic body and brewer provide powerful guarantee for long life and high stability under the commercial condition.



Smooth and hot milk frothing system makes the foam smoothly. Both milk and milk powder are available. It can be easily cleaned by self-clean function.



Ceramic flat-type blads, accurately grind the beans into unified-size powder, bringing out unique flavor.



The 10.1" touch panel is easy to use, direct and efficient. Pictures and videos are replacable which make advertising available for customers.

### Configuration

Configuration	Coffeebar Plus (●Standard ○Optional)
4L Water Tank	•
Tap Water Supply	•
E-payment	0
Dual Boiler system	•
Dual Pump system	•
Grinder	1个
Powder system	•
Separated Hot Water Dispenser	•
Display Configuration	Capacitive Touch screen
Display Size	10.1″
Display Shape	Lateral
Milk Coffee	•
Customize Beverage	•
Beverage Variety	24
Customize Interface	•
Mental Brew Unit	•
Brewer movability	•
Milk System time clean	•
Milk System Automatic Clean	•
Optional Color	•

#### Product introduction

Coffeebar is small in size but big on flavor. With their compact size and elegant looking, these machines compliment a variety of environments such as convinient store, small offices, meeting rooms etc..., could be vending coffee machines also.

#### Capacity

Hourly output based on DIN18873-2

A	Advised daily output		Coffeebar Plus
	Advised daily output		200 cups
	Hourly output	Espresso (M:50ml)	100cups
		Americano (M:210ml)	80cups
0 4		Cappuccino (M:200ml)	80cups
ŀ	Hourly hot water output		30L
	Water tank capacity		4L
- 1	Beans hopper capacity		1500g
F	Powder hopper capacity		Milk Powder 1200g/Chocolate Powder 2000g
Gr	Grounds container capacity		70pcs (10g/pc)
	Drip tray capacity		1.5L

#### Technical sheet

Technical Figures	Coffeebar Plus
Coffee machine	220-240V~ 50/60Hz 2700-3100W
Connection tube set	G3/4' change into G3/8' length 1.5M metal tube
Water pressure range	Max.0.6MPa
Coffee machine (W*D*H)	34 * 54.5 * 62 cm
N.W	26.5 kg





Coffeebar Plus

